

No	Name	Value(Range)	Comment
1-3	Startsequence	'M\$<'	
4	Nr of Data Bytes	16	8 Channel*2Byte
5	Message Type	200	"MSP_SET_RAW_RC"
6-7	Roll	1000-2000	6:low byte, 7:high byte
8-9	Nick	1000-2000	8:low byte, 9:high byte
10-11	Yaw	1000-2000	10:low byte, 11:high byte
12-13	Thrust	1000-2000	12:low byte, 13:high byte
14-15	Aux1	1000-2000	14:low byte, 15:high byte
16-17	Aux2	1000-2000	16:low byte, 17:high byte
18-19	Aux3	1000-2000	18:low byte, 19:high byte
20-21	Aux4	1000-2000	20:low byte, 21:high byte
22	Checksum	0-255	Bytewise XOR of 4-21